



## LED ZY-Tube



This T8 LED tube can work with or without a ballast, but wire directly to AC100-277V input . So it is a fantastic direct replacement tube as well as retrofit kit. It is compatible with more than 90 percent of electronic ballasts in the North American market. The wattages and Lumens for the tube are consistent for all sizes, making it ideal for big projects with different types of ballast.

### Features

- Reduces energy consumption by up to 40%.
- No UV emission.
- Suitable for dry and damp environments.
- T8 housing available.

### Application

- Warehouse / Industrial
- Parking Garages
- Office Buildings
- Commercial buildings

### Certifications



Made in the USA

### Specifications

MODEL#	LENGTH	WATTAGE	LUMENS	Average System Watts			Average Sytem Initial Lumens		
				Low Ballast Factor (0.78)	Normal Ballast Factor (0.88)	High Ballast Factor (1.10)	Low Ballast Factor (0.78)	Normal Ballast Factor (0.88)	High Ballast Factor (1.10)
ZY-L24T8-10W-600-3K	24	10	1400	11.5	12.5	13.5	1437	1550	1680
ZY-L24T8-10W-600-4K	24	10	1400	11.5	12.5	13.5	1437	1550	1680
ZY-L24T8-10W-600-5K	24	10	1400	11.5	12.5	13.5	1437	1550	1680
ZY-L48T8-15W-1200-3K	48	15	2100	16.5	17.5	20.5	2069	2180	2560
ZY-L48T8-15W-1200-4K	48	15	2100	16.5	17.5	20.5	2069	2180	2560
ZY-L48T8-15W-1200-5K	48	15	2100	16.5	17.5	20.5	2069	2180	2560